



WT100-2P3439

W100-2

**MINIATURE PHOTOELECTRIC SENSORS** 





### Ordering information

Туре	Part no.
WT100-2P3439	6052373

Included in delivery: BEF-W100-A (1)

Other models and accessories → www.sick.com/W100-2

Illustration may differ



#### Detailed technical data

#### **Features**

Sensor/ detection principle	Photoelectric proximity sensor, Energetic
Dimensions (W x H x D)	11 mm x 31 mm x 20 mm
Housing design (light emission)	Rectangular
Sensing range max.	0 mm 1,200 mm <sup>1)</sup>
Sensing range	0 mm 750 mm <sup>1)</sup>
Type of light	Visible red light
Light source	LED <sup>2)</sup>
Light spot size (distance)	Ø 75 mm (1,000 mm)
Wave length	632 nm
Adjustment	Potentiometer (Sensing range)

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033).

### Mechanics/electronics

Supply voltage	10 V DC 30 V DC <sup>1)</sup>
Ripple	± 10 % <sup>2)</sup>
Current consumption	30 mA <sup>3)</sup>

<sup>1)</sup> Limit values.

 $<sup>^{2)}</sup>$  Average service life: 100,000 h at  $T_U$  = +25 °C.

 $<sup>^{2)}\,\</sup>mbox{May}$  not exceed or fall below  $\mbox{U}_{\mbox{\scriptsize V}}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{4)}</sup>$  Signal transit time with resistive load.

<sup>&</sup>lt;sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A = V<sub>S</sub> connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> B = output reverse-polarity protected.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

Switching output	PNP
Switching mode	Light/dark switching
Switching mode selector	Selectable via light/dark rotary switch
Signal voltage PNP HIGH/LOW	$U_V - 1.8 \text{ V/ca. } 0 \text{ V}$
Output current I <sub>max.</sub>	100 mA
Response time	$\leq$ 0.5 ms $^{4)}$
Switching frequency	1,000 Hz <sup>5)</sup>
Connection type	Connector M8, 3-pin
Circuit protection	A <sup>6)</sup> B <sup>7)</sup> D <sup>8)</sup>
Protection class	III
Housing material	Plastic, ABS/PC/POM
Optics material	Plastic, PMMA
Enclosure rating	IP67
Items supplied	Mounting bracket BEF-W100-A
Ambient operating temperature	-25 °C +55 °C
Ambient storage temperature	-40 °C +70 °C

<sup>1)</sup> Limit values.

## Safety-related parameters

MTTF <sub>D</sub>	954 years
<b>DC</b> <sub>avg</sub>	0%

## Classifications

ECI@ss 5.0	27270904
ECI@ss 5.1.4	27270904
ECI@ss 6.0	27270904
ECI@ss 6.2	27270904
ECI@ss 7.0	27270904
ECI@ss 8.0	27270904
ECI@ss 8.1	27270904
ECI@ss 9.0	27270904
ECI@ss 10.0	27270904
ECI@ss 11.0	27270904
ETIM 5.0	EC002719
ETIM 6.0	EC002719

 $<sup>^{2)}</sup>$  May not exceed or fall below  $\mathrm{U}_{\mathrm{V}}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A = V<sub>S</sub> connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> B = output reverse-polarity protected.

<sup>8)</sup> D = outputs overcurrent and short-circuit protected.

# WT100-2P3439 | W100-2

ETIM 7.0	EC002719
UNSPSC 16.0901	39121528


## Connection diagram

Cd-045

#### Characteristic curve

WT100-2, energetic


Function reserve



- $\ \textcircled{1}$  Sensing range on white, 90% remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6% remission

## Light spot size

#### Light spot size



## Sensing range diagram


#### WT100-2, energetic



- \*Close-up range at maximum sensitivity
- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6% remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90% remission

## Adjustments possible


#### W100-2




- ① LED indicator orange: switching output active
- ② LED indicator green: power on
- 3 Sensing range adjustment: potentiometer
- 4 Light/ dark rotary switch: L = light switching, D = dark switching

## Dimensional drawing (Dimensions in mm (inch))

WT100, WL100





- ① Threaded mounting hole M3
- ② Center of optical axis, receiver
- 3 Center of optical axis, sender
- 4 Connection
- ⑤ LED indicator orange: switching output active
- ⑥ LED indicator green: power on

#### Recommended accessories

Other models and accessories → www.sick.com/W100-2

	Brief description	Туре	Part no.		
Mounting bra	Mounting brackets and plates				
	Mounting bracket for wall mounting, stainless steel, mounting hardware included	BEF-W100-A	5311520		
	Mounting bracket for floor mounting, steel, zinc coated, mounting hardware included	BEF-W100-B	5311521		
Plug connecto	Plug connectors and cables				
	Head A: female connector, M8, 3-pin, straight, A-coded Head B: Flying leads Cable: Sensor/actuator cable, PVC, unshielded, 5 m	YF8U13- 050VA1XLEAX	2095884		
	Head A: male connector, M8, 3-pin, straight Head B: - Cable: unshielded	STE-0803-G	6037322		

## SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

